PresenceLight 180

Item no.: 2000050



Präsenzmelder & Bewegungsmelder Wandmontage innen

Description

- Passive infra-red presence detector for wall installation
- Half-round detection area 180°, Ø 16 m, (100 m²)
- Mixed light measurement
- Light switch output (relay, 230 V)
- Automatic lighting control
- Lighting control with light threshold value and self-learning switch-off delay
- Pulse function for staircase time switch
- Can be configured remotely



Technical data

	PresenceLight 180	
Operating voltage	230 V AC	
Frequency	50 Hz	
Installation height	1.6 – 2.2 m	
Installation type	Wall installation	
Colour	White	
Switching output	Light	
Power consumption	~0.9 W	
Light measurement	Mixed light measurement	
Setting range brightness	10 – 1500 lx	
Light switch-off delay	Pulse (0,5 s), 10 s-20 min	
Type of contact light	Relay 230 V	
Lamps	Incandescent/halogen lamps, fluorescent lamps, Energy saving lamps, LEDs	
Resistive load	1400 W	
Incandescent/halogen lamp load	1200 W	


PresenceLight 180		
960 VA (cos f = 0,8), 580 VA (cos f = 0,5)		
max. 250 A / 200 μs		
10 x (1 x 58 W), 5 x (2 x 58 W), 16 x (1 x 36 W), 8 x (2 x 36 W), 16 x (smaller than 36 W)		
25 W		
70 W		
80 W		
Screw terminals		
2 x 2,5 mm²		
70 x 70 mm		
Ø 55 mm (NIS, PMI)		
100 m² (ø 16 m 180°)		
180°		
-20°C 50°C		
IP 54		

PresenceLight 180

Item no.: 2000050





Connection example



Detection range for planning applications at a temperature of 21 °C

Mounting height (A)	Walking (T)	Sitting (S)	
2.2 m	100 m² 8 m	25 m² 7 m x 3.5 m	







PresenceLight 180


Item no.: 2000050




Scale drawings









Accessories

clic

Item no.: 9070515

Cover frame PresenceLight 180

Item no.: 9070629

Cover frame PresenceLight 180 SR

Item no.: 9070627



QuickSafe Item no.: 9070531



Cover frame PresenceLight 180 BK

Item no.: 9070628



Surface frame PresenceLight Item no.: 9070513

